

# پارس مکاترونیک

تامین تجهیزات، مشاوره و اجرا ، آموزش  
سیستمهای اتوماسیون صنعتی و رباتیک



کاتالوگ محصولات



High-performance Automation Initiator



# PM SERIES



**Programmable Logic Controller**  
Product Catalog



## PM PLC CPU 224/226



CPU224

CPU226

### I Characteristic I

- high-speed computing and data processing : Boolean execution speed: 0.08 μs per instruction
- Larger user storage: Program storage: 20K; User data storage: 10K
- Built-in PID, having no limitations on the number of the channels, making it more convenient for users to realize the PID control of more channels
- Apply FLASH's long-time data-holding on power-off, no need of power supply, can save data for 10 years
- Unique AES Iterative encryption algorithm, which protects clients' intellectual property
- Communication ports: 2 RS-485, both support PPI protocol

### Specifications:

|                       | Model  | CPU224 DC/DC/DC   | CPU224 AC/DC/RLY   | CPU226 DC/DC/DC  | CPU226 AC/DC/RLY   |
|-----------------------|--|---|--|------------------|--|
| Dimensions(W X H X D) | 140 x 80 x 62 mm   | 140 x 80 x 62 mm  | 196 x 80 x 62 mm   | 196 x 80 x 62 mm | 196 x 80 x 62 mm   |
| Power consume         | 7 W  | 10 W  | 11 W   | 17 W             | 24K  |
| Memory                | With run mode edit<br>Without run mode edit<br>Date memory   | 20K<br>20K<br>10K   |  |                  | 24K<br>24K<br>10K  |
| I/O                   | Local digital inputs<br>Local digital outputs<br>Digital I/O image size<br>Analog I/O image size<br>Expansion modules allowed (Max)<br>Intelligent modules allowed (Max)<br>Pulse catch inputs<br>High-speed counters<br>Single phase<br>Two phase<br>Pulse outputs            | 14 inputs<br>10 outputs<br>256(128 inputs/128 outputs)<br>64(32 inputs/32 outputs)<br>7 modules<br>7 modules<br>14<br>6 counters total<br>6 at 30KHz<br>4 at 20KHz<br>2 at 30KHz  | 24 inputs<br>16outputs<br>256 (128 inputs/128 outputs)<br>64(32 inputs/32 outputs)<br>7 modules<br>7 modules<br>24<br>6counters total<br>6 at 30KHz<br>4 at 20KHz<br>2 at 30KHz                                  |                  | 24 inputs<br>16outputs<br>256 (128 inputs/128 outputs)<br>64(32 inputs/32 outputs)<br>7 modules<br>7 modules<br>24<br>6counters total<br>6 at 30KHz<br>4 at 20KHz<br>2 at 30KHz                                  |
| General               | Timer<br>Counters<br>Internal memory bits stored on power down   | Total number:256(1ms:4;10ms:16;100ms:236)<br>256  | Total number:256(1ms:4;10ms:16;100ms:236)<br>256   |                  | Total number:256(1ms:4;10ms:16;100ms:236)<br>256   |
| Communications        | Time interrupts<br>Edge interrupts<br>Analog adjustment<br>Boolean execution speed<br>Real Time Clock<br>Ports<br>PPI Baud Rates<br>Freeport Baud Rates<br>Max. cable length per segment<br>Max. number of stations<br>Max. number of masters<br>Peer to peer(PPI Master Mode) | 2 with1ms resolution<br>4 up and/or 4 down<br>2 with 8 bit resolution<br>0.08 μs per instruction<br>Built-in<br>2 RS-485 ports, within1standard PPI port<br>9.6,19.2 and 187.5K baud<br>1.2kbaud to 115.2K baud<br>With isolated repeater:1000 m up to 187.5kbaud, 1200 m up to 38.4kbaud<br>Without isolated repeater: 50 m<br>32 per segment, 126 per network<br>32<br>No | 2 with1ms resolution<br>4 up and/or 4 down<br>2 with 8 bit resolution<br>0.08 μs per instruction<br>Built-in<br>2 RS-485 ports, within1standard PPI port<br>9.6,19.2 and 187.5K baud<br>1.2K baud to 115.2K baud |                  | 2 with1ms resolution<br>4 up and/or 4 down<br>2 with 8 bit resolution<br>0.08 μs per instruction<br>Built-in<br>2 RS-485 ports, within1standard PPI port<br>9.6,19.2 and 187.5K baud<br>1.2K baud to 115.2K baud |

## 8 Content

### PM 200 series PLC


|  |       |
|--|-------|
| 1)、PM 200 CPUs                               | 10-13 |
| 2)、PM 200 Digital Expansion Modules          | 14-19 |
| 3)、PM 200 Analog Expansion Modules           | 20-31 |
| 4)、PM 200 TC/RTD Mудules                     | 24-27 |
| 5)、EM277 PROFIBUS-DP Module                  | 28    |
| 6)、IM260 PROFIBUS-DP Interface Module        | 29    |
| 7)、Three-Phase AC & Leakage Detection Module | 30    |
| 8)、Four-input High-speed & High Precision    | 31    |
| 9)、PM200 Special Accessories                 | 32-33 |

## Characteristics


| 项目                                | CPU224 DC/DC/DC  | CPU224 AC/DC/Relay  | CPU226 DC/DC/DC   | CPU226 AC/DC/Relay  |
|-----------------------------------|--|---|---|---|
| Power                             | Input voltage<br>20.4 to 28.8V DC  | 85 to 264 VAC(47 to 63Hz)   | 20.4 to 28.8V DC  | 85 to 264V AC(47 to 63Hz)   |
|                                   | Input current<br>110mA while CPU only at 24 V DC<br>700mA while Max. load at 24 V DC | 60/30mA while CPU only at 120/240V AC<br>200/100mA while Max. load at 120/240V AC | 110mA while CPU only at 24 V DC<br>700mA while Max. load at 24 V DC | 60/30mA while CPU only at 120/240V AC<br>200/100mA while Max. load at 120/240V AC |
|                                   | Inrush current<br>12A at 28.8 V DC   | 20A at 264V AC  | 12A at 28.8 V DC  | 20A at 264V AC  |
|                                   | Isolation(field to logic)<br>Not isolated  | 1500V AC  | Not isolated  | 1500V AC  |
|                                   | Hold up time(loss of power)<br>10ms at 24 V DC                                       | 10ms at 120/240 V AC  | 10ms at 24 V DC   | 10ms at 120/240 VAC   |
|                                   | Sensor voltage<br>L+ minus 5 V   | 20.4 to 28.8VDC   | L+ minus 5 V  | 20.4 to 28.8VDC   |
|                                   | Current limit<br>1.5A peak,thermal limit non-destructive                             |   | 1.5A peak,thermal limit non-destructive                             |   |
|                                   | Ripple noise (sensor to logic)<br>Derived from input power                           | Less than 1V peak-to-peak   | Derived from input power  | Less than 1V peak-to-peak   |
|                                   | Isolation (sensor to logic)<br>Not isolated  |   |   |   |
|                                   | Built-in digital input<br>14 inputs  |   | 24 inputs   |   |
| CPU Digital Input Specifications  | Input type<br>PNP/NPN  |   |   |   |
|                                   | Rated voltage<br>24V DC, 4mA   |   |   |   |
|                                   | Max. continuous permissible voltage<br>30V DC  |   |   |   |
|                                   | Surge voltage<br>35V DC, 0.5s  |   |   |   |
|                                   | Logic "1" voltage range<br>15V~30V DC  |   |   |   |
|                                   | Logic "0" voltage range<br>0~5V DC   |   |   |   |
|                                   | Input delay<br>Selectable (0.2 to 12.8ms)  |   |   |   |
|                                   | Connection of 2-wire proximity sensor (Bero)   |   |   |   |
|                                   | Premissible leakage current (Max.)<br>1mA  |   |   |   |
|                                   | Isolation (field to logic)<br>Yes  |   |   |   |
| CPU Digital output Specifications | Isolation<br>Optical galvanic  | 500 VAC for 1 minute  |   |   |
|                                   | Isolation groups<br>Refer to Wiring diagram  |   |   |   |
|                                   | High Speed Counter (HSC) input rate<br>Logic=15~30V DC                               | 20K Hz (Single phase), 10K Hz (Two phase)   |   |   |
|                                   | (HSC) input rate<br>Logic1=15~26V DC   | 30K Hz (Single phase), 20K Hz (Two phase),  |   |   |
|                                   | Inputs on simultaneously<br>All  |   |   |   |
|                                   | Cable length Max<br>Cable  | 500m normal inputs  |   |   |
|                                   | Shielded   | 50m HSC inputs  |   |   |
|                                   | Unshielded   | 300m normal inputs  |   |   |
|                                   | Built-in outputs<br>10 outputs   |   | 16 outputs  |   |
|                                   | Output type<br>Solid State-MOSFET(Sourcing)  | Dry contact   | Solid State-MOSFET(Sourcing)  | Dry contact   |
| CPU Analog Input Specifications   | Rated voltage<br>24V DC  | 24V DC or 250V AC   | 24V DC  | 24V DC or 250V AC   |
|                                   | Voltage range<br>20.4 to 28.8 VDC  | 5 to 30V DC or 5 to 250V AC   | 20.4 to 28.8 VDC  | 5 to 30V DC or 5 to 250V AC   |
|                                   | Surge current (Max.)<br>8A, 100ms  | 5A for 4s at 10% duty cycle   | 8A, 100ms   | 5A for 4s at 10% duty cycle   |
|                                   | Logic "1" (Min)<br>20 V DC,at maximum current  | -   | 20 V DC,at maximum current  | -   |
|                                   | Logic "0" (Max)<br>0.1 V DC with 10KΩ load   | -   | 0.1 V DC with 10KΩ load   | -   |
|                                   | Rated current per point(Max.)<br>0.75A   | 2.0A  | 0.75A   | 2.0A  |
|                                   | Rated current per common (Max)<br>6 A  | 10A   | 6 A   | 10A   |
|                                   | Leakage current (Max)<br>10µA  | -   | 10µA  | -   |
|                                   | Lamp load (Max)<br>5 W   | 30W DC ; 200W AC  | 5 W   | 30W DC ; 200W AC  |
|                                   | Inductive clamp voltage<br>L+ minus 48 V DC, 1w dissipation                          | -   | L+ minus 48 V DC, 1w dissipation                                    | -   |
| CPU Analog Output Specifications  | On State resistance (contact)<br>0.3Ω Typical(0.6Ω max.)                             | 0.2Ω(max. when new)   | 0.3Ω Typical(0.6Ω max.)   | 0.2Ω(max. when new)   |
|                                   | Optical (galvanic, field to logic)<br>500 VAC for 1 minute                           | -   | 500 VAC for 1 minute  | -   |
|                                   | Isolation<br>Logic to contact  | 500 VAC for 1 minute  | -   | 500V AC for 1 minute  |
|                                   | Resistance (logic to contact)<br>100 MΩ  | -   | -   | 100 MΩ  |
|                                   | Isolation groups<br>Refer to wiring diagram  |   | Refer to wiring diagram   |   |
|                                   | Off to on<br>2µs(Q0.0, Q0.1),15µs(Other)   | -   | 2µs(Q0.0, Q0.1),15µs(Other)   | -   |
|                                   | On to off<br>10µs(Q0.0, Q0.1),130µs(Other)   | -   | 10µs(Q0.0, Q0.1),130µs(Other)                                       | -   |
|                                   | Switching<br>-   | 10ms  | -   | 10ms  |
|                                   | Pulse frequency (Max.)<br>20KHz(Q0.0 and Q0.1)                                       | 1Hz   | 20KHz(Q0.0 and Q0.1)  | 1Hz   |
|                                   | Lifetime mechanical cycles<br>-  | 10,000,000(No load)   | -   | 10,000,000(No load)   |
| CPU Analog Contact Specifications | Lifetime contacts<br>-   | 100,000(No load)  | -   | 100,000(No load)  |
|                                   | Outputs on simultaneously<br>All at 60°C(horizontal)                                 |   | All at 60°C(horizontal)   |   |
|                                   | All at 50°C (Vertical)   |   | All at 50°C (Vertical)  |   |
|                                   | Connecting two outputs in parallel<br>Yes, only outputs in same group                | No  | Yes, only outputs in same group                                     | No  |
|                                   | Cable length(Max)<br>Shielded  | 500 m   |   |   |
|                                   | Unshielded   | 150 m   |   |   |
|                                   | Order number   | PM 214-1AD23-0XB0   | PM 214-1BD23-0XB0   | PM 216-2AD23-0XB0   |
|                                   |  |   | PM 216-2BD23-0XB0   |   |

## CPU224

## CPU224 Structure




## CPU224 Wiring Diagram





## CPU226

## CPU226 Structure



## CPU226 Wiring Diagram




## CPU224, CPU226 specification


1. CPU224 DC/DC/DC wiring diagram is shown as picture 2, CPU226 DC/DC/DC wiring diagram is shown as picture 5. The two CPUs are 24 VDC power supply, please shut off the power when connecting.
2. CPU224 AC/DC/RLY wiring diagram is shown as picture 3, CPU226 AC/DC/RLY wiring diagram is shown as picture 6. The two CPUs are 120/240 v AC power supply. You must shut off the power when connecting. Please pay attention to safety, do not use hand to touch power supply terminals.
3. the using of PPI adapter or CP 5611 PPI port is connected as picture 1 or picture 4.
4. if you install an external extension module, please connect extension module on port of picture 1 and picture 4. A CPU224 or a CPU226 can connect up to seven extension modules.
5. Install STEP 7 MicroWIN software and open, double-click the communication options, click refresh to find information on the CPU. If CPU224 or CPU226 connects external extension modules, double click on the icon of CPU, then you can see information of the extension modules.

## Specifications:

| Model:   | EM 221 8 inputs                                     | EM 221 16 inputs                                     | EM 221 32 inputs                                     |
|--|---|--|--|
| Product Picture                                      |   |  |  |
| Product Description                                  | 8DI, 24VDC;<br>Optical isolation with high immunity | 16DI, 24VDC;<br>Optical isolation with high immunity | 32DI, 24VDC;<br>Optical isolation with high immunity |
| From bus current consumption                         | 40mA  | 85mA   | 140mA  |
| Power loss   | 2W  | 3W   | 5.2 W  |
| Number of digital inputs                             | 8   | 16   | 32   |
| Input type   | PNP/NPN   |  |  |
| Input voltage range                                  | 24V DC 4mA  |  |  |
| Maximum input voltage                                | 30V DC  |  |  |
| Surge voltage  | 35V DC , 0.5s                                       |  |  |
| Logic 0 signal                                       | 0~5 V DC  |  |  |
| Logic 1 signal                                       | 15~30V DC   |  |  |
| Input delay(max)                                     | 4.5ms   |  |  |
| Optical isolation(Galvanic)<br>(Field Side to Logic) | 500V AC for 1 minute                                |  |  |
| Premissible leakage current(Bero)                    | 1mA   |  |  |
| Cable Length   | Shielded  |  |  |
|  | Unshielded  |  |  |
| Dimensions(W x H x D)                                | 46 x 80 x 62 mm                                     | 71.2 x 80 x 62 mm                                    | 137.5 x 80 x 62 mm                                   |
| Order Number   | PM 221-1BF22-0XA0                                   | PM 221-1BH22-0XA0                                    | PM 221-1BL22-0XA0                                    |

## Wiring Diagram






PM 221-1BL22-0XA0



PM 222-1BF22-0XA0




PM 222-1BH22-0XA0

## PM 200 DO MODULES


### Specifications:

| Model:   | EM 222 8 outputs Transistor  | EM 222 8 outputs Relay                         | EM 222 16 outputs   | EM 222 16 outputs Relay   | EM 222 32 outputs   |
|--|--|--|---|---|---|
| Product Picture                                  |  |  |   |   |   |
| Product Description                              | 8DO, 24V DC;<br>Transistor;<br>Optical isolation with<br>high immunity | 8DO, 24V DC/250V AC<br>Relay;<br>high immunity | 16DO, 24V DC;<br>Transistor;<br>Optical isolation<br>with high immunity | 16DO, 24V DC/250V AC<br>Relay;<br>Optical isolation<br>with high immunity | 32DO, 24V DC;<br>Transistor;<br>Optical isolation<br>with high immunity |
| From bus current consumption                     | 65mA   | 60mA   | 110mA   | 98mA  | 140mA   |
| Power loss                                       | 2W   | 3W   | 3W  | 3W  | 5.2W  |
| Number of DI                                     | 8  | 8  | 16  | 16  | 32  |
| Input type                                       | Transistor   | Relay  | Transistor  | Relay   | Transistor  |
| Isolation  | Optical coupler  | Relay  | Optical coupler   | Relay   | Optical coupler   |
| Rated voltage                                    | 24 V DC  | 24 V DC or 250 V AC                            | 24V DC  | 24V DC or 250V AC   | 24V DC  |
| Input voltage range                              | 20.4~28.8VDC   | 5~30V DC、20~250V AC                            | 20.4~28.8VDC  | 5~30V DC, 20~250V AC  | 20.4~28.8VDC  |
| Rated current                                    | 0.75A  | 2.0A   | 0.75A   | 2.0A  | 0.75A   |
| Lamp load  | 5W   | 30W DC/200W AC                                 | 5W  | 30W DC/200W AC  | 5W  |
| Cable Length                                     | Shielded<br>500m<br>Unshielded<br>150m                                 |  |   |   |   |
| Switching frequency                              | /  | 1 Hz   | /   | 1Hz   | /   |
| Lifetime contact mechanical                      | /  | 10,000,000                                     | /   | 10,000,000  | /   |
| Lifetime contact mechanical( rated load voltage) | /  | 100,000  | /   | 100,000   | /   |
| Dimensions(W x H x D)                            | 46 × 80 × 62 mm  | 46 × 80 × 62 mm                                | 71.2 × 80 × 62 mm   | 71.2 × 80 × 62 mm   | 137.5 × 80 × 62 mm  |
| Order Number                                     | PM 222-1BF22-0XA0  | PM 222-1HF22-0XA0                              | PM 222-1BH22-0XA0   | PM 222-1HH22-0XA0   | PM 222-1BL22-0XA0   |


### Wiring Diagram



PM 222-1BF22-0XA0



PM 222-1HF22-0XA0






PM 222-1BL22-0XA0

## PM 200 DI/DO Modules

| Model  | EM223 4DI/4DO  | EM223 4DI/4DO, Relay  | EM223 8 DI/8 DO   | EM223 8 DI/8 DO, Relay   |
|--|--|---|---|--|
| Product Picture                                  |  |   |   |  |
| Product Description                              | 4DI 24VDC/4 DO<br>24VDC,<br>Transistor,<br>Optical isolation w ith<br>high immunity. | 4DI 24VDC/4 DO 24<br>VDC/250VAC,<br>Relay isolation w ith high<br>immunity. | 8DI 24VDC/8DO,24VDC<br>Transistor;<br>Optical isolation w ith high<br>immunity. | 4DI 24VDC/4 DO 24 VDC<br>/250VAC,<br>Relay isolation w ith high<br>immunity. |
| Technical Specification                          |  |   |   |  |
| From bus current consumption                     | 40mA   | 40mA  | 80mA  | 80mA   |
| Power loss                                       | 2W   | 2W  | 3W  | 3W   |
| Input Features                                   |  |   |   |  |
| Number of digital inputs                         | 4  | 4   | 8   | 8  |
| Input voltage                                    | 24V DC,4mA   | 24V DC,4mA  | 24V DC,4mA  | 24V DC,4mA   |
| Logic 0 signal                                   | 0~5V DC  | 0~5V DC   | 0~5V DC   | 0~5V DC  |
| Logic 1 signal                                   | 15~30V DC  | 15~30V DC   | 15~30V DC   | 15~30V DC  |
| (Max.) Input Delay Time                          | 4.5ms  | 4.5ms   | 4.5ms   | 4.5ms  |
| Signal input type:                               | PNP/NPN  | PNP/NPN   | PNP/NPN   | PNP/NPN  |
| Optical isolation<br>(Galvanic) (field to logic) | 500 VAC for 1 minute   |   |   |  |
| Cable Length                                     | 500m(Shielded); 300m(Unshielded);  |   |   |  |
| Output Features                                  |  |   |   |  |
| Number of digital outputs                        | 4  | 4   | 8   | 8  |
| Output type                                      | Transistor   | Relay   | Transistor  | Relay  |
| Isolation  | Optical coupler  | Relay   | Optical coupler   | Relay  |
| Output voltage                                   | 24V DC   | 24V DC or 250VAC  | 24V DC  | 24V DC or 250VAC   |
| Output voltage range                             | 20.4~28.8V DC  | 5~30VDC/20~250V AC  | 20.4~28.8V DC   | 5~30V DC/20~250V AC  |
| Output Current                                   | 0.75A  | 2.0A  | 0.75A   | 2.0A   |
| Lamp load  | 5W   | 30W DC/200W AC  | 5W  | 30W DC/200W AC   |
| Lifetime mechanical                              | /  | 10,000,000  | /   | 10,000,000   |
| Lifetime contacts(Rated load voltage)            | /  | 100,000   | /   | 100,000  |
| Cable Length                                     | 500m(Shielded); 300m(Unshielded);  |   |   |  |
| Dimensions(W x H x D)                            | 46×80×62(mm)   | 46×80×62(mm)  | 71.2×80×62(mm)  | 71.2×80×62(mm)   |
| Order Number                                     | PM 223-1BF22-0XA0  | PM 223-1HF22-0XA0   | PM 223-1BH22-0XA0   | PM 223-1PH22-0XA0  |



## Wiring Diagram



## PM 200 DI/DO Modules

| Model   | EM 223 16 inputs/16 outputs                                      | EM 223 16 inputs/16 outputs Relay                                      |
|---|--|--|
| Product Picture                                     |  |  |
| Product Description                                 | 16DI 24VDC/16DO 24 VDC<br>Optical isolation w ith high immunity. | 16DI 24VDC/16DO 24 VDC/250VAC,<br>Relay isolation w ith high immunity. |
| Input Feature                                       |  |  |
| From bus current consumption                        | 140mA  | 140mA  |
| Power loss  | 5.2W   | 5.2W   |
| Digital Input Specification                         |  |  |
| Number of digital inputs                            | 16   | 16   |
| Input voltage                                       | 24 VDC   | 24 VDC,4mA   |
| Logic 0 signal                                      | 0~5 VDC  | 0~5 VDC  |
| Logic 1 signal                                      | 15~30 VDC  | 15~30 VDC  |
| Maximum Input Delay Time                            | 4.5ms  | 4.5ms  |
| Signal input type:                                  | PNP/NPN  | PNP/NPN  |
| Optical isolation(Galvanic)                         | 500 V AC for 1 minute  | 500 V AC for 1 minute  |
| Cable Length  | 500m(Shielded);300m (unshielded)                                 |  |
| Output Feature                                      |  |  |
| Number of digital outputs                           | 16   | 16   |
| Output type   | Transistor   | Relay  |
| Isolation   | Optical coupler  | Relay  |
| Output voltage                                      | 24 VDC   | 24 VDC or 250VAC   |
| Output voltage range                                | 20.4~28.8V DC  | 5~30 VDC/20~250V AC  |
| Output Current                                      | 0.75A  | 2.0A   |
| Lamp load   | 5W   | 30W DC/200W AC   |
| Lifetime contact mechanical                         | /  | 10,000,000   |
| Lifetime contact mechanical<br>(rated load voltage) | /  | 100,000  |
| Cable Length  | 500m(Shielded);300m (unshielded)                                 |  |
| Dimensions(W x H x D)(mm)                           | 137.5×80×62  | 137.5×80×62  |
| Order Number  | PM 223-1BL22-0XA0  | PM 223-1DL22-0XA0  |

## Wiring Diagram



## PM 200 AI Modules

## Specifications:

| Model   | EM231<br>4 inputs × 12 bits                               | EM231<br>8 inputs × 14 bits                               | EM231<br>8 inputs × 14 bits                               |
|---|---|---|---|
| Picture                                       |   |   |   |
| Product Description                           | 4AI,24V DC;<br>Resolution:12bits;<br>High immunity,stable | 8AI,24V DC;<br>Resolution:14bits;<br>High immunity,stable | 8AI,24V DC;<br>Resolution:14bits;<br>High immunity,stable |
| <b>Technical Specification</b>                |   |   |   |
| From bus current consumption                  | 20mA  | 20mA  | 20mA  |
| From L+ current consumption                   | 60mA  | 60mA  | 60mA  |
| Power loss                                    | 2W  | 2W  | 2W  |
| Number of analog Inputs                       | 4   | 8   | 8   |
| Input type                                    | Differential  | Differential  | Differential  |
| Voltage input range: Unipolar                 | 0~5v,0~10V  | 0~5v,0~10V  | 0~5v,0~10V  |
| Voltage input range: Bipolar                  | ±2.5V,±5V   | ±5V,±10V  | ±5V,±10V  |
| input range:current                           | 0~20mA  | 0~20mA,± 20mA   | 0~20mA,± 20mA   |
| Resolution                                    | 12 bit  | 14bit   | 14bit   |
| Bipolar,full-scale range                      | -32,000 to +32,000  | -32,000 to +32,000  | -32,000 to +32,000  |
| Unipolar, full-scale range                    | 0 to +32,000  | 0 to +32,000  | 0 to +32,000  |
| Cable Length (unShielded)                     | 300m  | 300m  | 300m  |
| Input impedance                               | ≥10M Ω Voltage Input                                      | ≥10M Ω Voltage Input                                      | ≥10M Ω Voltage Input                                      |
|   | 250 Ω Current Input                                       | 250 Ω Current Input                                       | 250 Ω Current Input                                       |
| Isolation tested for contact (field to logic) | <2000V  | No  | No  |
| Analog to digital conversion time             | <250μs  | <250μs  | <200μs  |
| Common-mode rejection                         | 40db,DC to 60Hz   | 40db,DC to 60Hz   | 80dB  |
| Common-mode voltage                           | Signal voltage + Common-mode voltage≤12V                  | Signal voltage + Common-mode voltage≤12V                  | Signal voltage + Common-mode voltage≤12V                  |
| Maximum input voltage                         | 30V DC  | 30V DC  | 30V DC  |
| Maximum input current                         | 32mA  | 32mA  | 32mA  |
| Address of the interval                       | AIW   | AIW   | VW  |
| Dimensions(W x H x D)(mm)                     | 71.2×80×62  | 71.2×80×62  | 71.2×80×62  |
| Order Number                                  | PM 231-0HC22-0XA0   | PM 231-0HF22-0XA0   | PM 231-0HH32-0XA0   |

## PM 200 analog input modules DIP switches configuring table

| Switch Location<br>Modules model | SW 1 | SW 2 | SW 3 | SW 4 | SW 5 | SW 6 | Full inputs |
|----------------------------------|------|------|------|------|------|------|-------------|
| PM 231-0HC22-0XA0                | ON   | OFF  | ON   |      |      |      | 0 ~ 10V     |
|                                  | ON   | ON   | OFF  |      |      |      | 0 ~ 5V      |
|                                  | ON   | ON   | OFF  |      |      |      | 0 ~ 20mA    |
|                                  | OFF  | OFF  | ON   |      |      |      | ± 5V        |
|                                  | OFF  | ON   | OFF  |      |      |      | ± 2.5V      |
| PM 231-0HF22-0XA0                | OFF  | OFF  | ON   | OFF  | OFF  |      | 0 ~ 10V     |
|                                  | OFF  | OFF  | ON   | ON   | OFF  |      | 0 ~ 5V      |
|                                  | ON   | ON   | ON   | ON   | ON   |      | 0 ~ 20mA    |
|                                  | OFF  | OFF  | OFF  | OFF  | OFF  |      | ± 10V       |
| PM 231-0HH32-0XA0                | OFF  | OFF  | OFF  | ON   | OFF  |      | ± 5V        |
|                                  | OFF  | OFF  | OFF  | ON   | ON   |      | ± 20mA      |
|                                  | ON   | ON   | OFF  | ON   | ON   |      | 0 ~ 10V     |

★ Remark: After DIP switches are set up, it will be effective once the PLC is powered.

### ■ Address configuration of PM 200 analog expansion modules




For example, software address configuration of PM 231-0HH32-0XA0 is VW area. Different location in rail should have different address value. Calculation formula: VW(64\*i+2\*j).

Remark: "i" is the location of modules. "j" is the series number of input channel. "i" and "j" start from 0 and each module has 8 input channels.

The table of PM 231-0HH32-0XA0 address configuration

| Location value in Rail | Channel 0 | Channel 1 | ... | Channel 7 |
|------------------------|-----------|-----------|-----|-----------|
| Location 0             | VW0       | VW2       | ... | VW14      |
| Location 1             | VW64      | VW66      | ... | VW78      |
| Location 2             | VW128     | VW130     | ... | VW142     |
| Location 3             | VW192     | VW194     | ... | VW206     |
| Location 4             | VW256     | VW258     | ... | VW270     |
| Location 5             | VW320     | VW322     | ... | VW334     |
| Location 6             | VW384     | VW386     | ... | VW398     |

### ■ Wiring Diagram





### PM 200 AO Modules

#### Specifications:

| Model                        | EM232 2 outputs ×12bits  | EM232 4 outputs ×12bits  |
|------------------------------|--|--|
| Picture                      | A photograph of the EM232 2 outputs ×12bits module, showing its physical appearance. | A photograph of the EM232 4 outputs ×12bits module, showing its physical appearance.               |
| Product Description          | 2AO;<br>12 bits resolution voltage output;<br>11 bits resolution current output      | 4AO; Resolution:16bits;<br>12 bits resolution voltage output;<br>11 bits resolution current output |
| <b>Input Feature</b>         |  |  |
| From bus current consumption | 20mA   | 22mA   |
| From L+ current consumption  | 70mA   | 92mA   |
| Pow er loss                  | 2W   | 2.5W   |
| <b>Output Feature</b>        |  |  |
| Number of analog output      | 2  | 4  |
| Output voltage range         | -10~+10V   | -10~+10V   |
| Output current range         | 0~20mA   | 0~20mA   |
| Load impedance               |  |  |
| ·for voltage outputs         | Min:5KΩ  | Min:5KΩ  |
| ·for current outputs         | Max:0.5KΩ  | Max:0.5KΩ  |
| Resolution                   | 12 bits voltage output;<br>11 bits current output                                    | 12 bits voltage output;<br>11 bits current output  |
| Data w ord format            |  |  |
| ·Displayable:voltage output  | -32, 000~+32, 000  | -32, 000~+32, 000  |
| ·Displayable:current output  | 0~32, 000  | 0~32, 000  |
| Basic tolerance              | ±0.5% of full range  | ±0.5% of full range  |
| Dimensions(W x H x D)(mm)    | 46×80×62   | 71.2×80×62   |
| Order Number                 | PM 232-0HB22-0XA0  | PM 232-0HD22-0XA0  |

### ■ Wiring Diagram




## PM 200 AI/AO Modules

## Specifications:

| Model                        | EM235 4 AI /1 AO ×12bits   |
|------------------------------|--|
| Picture                      |  |
| Product Description          | 4AI; 1AO; 12 bits resolution voltage output; 11 bits resolution current output |
| Input Feature                |  |
| From bus current consumption | 30mA   |

## Wiring Diagram



PM 235-0KD22-0XA0

## DIP switches configuring table

| Modules model     | Switch Location | SW 1 | SW 2 | SW 3 | SW 4 | SW 5 | SW 6      | Full inputs |
|-------------------|-----------------|------|------|------|------|------|-----------|-------------|
| PM 235-0KD22-0XA0 | ON              | OFF  | OFF  | ON   | OFF  | ON   | 0 ~ 50mV  |             |
|                   | OFF             | ON   | OFF  | ON   | OFF  | ON   | 0 ~ 100mV |             |
|                   | ON              | OFF  | OFF  | OFF  | ON   | ON   | 0 ~ 500mV |             |
|                   | OFF             | ON   | OFF  | OFF  | ON   | ON   | 0 ~ 1V    |             |
|                   | ON              | OFF  | OFF  | OFF  | OFF  | ON   | 0 ~ 5V    |             |
|                   | ON              | OFF  | OFF  | OFF  | OFF  | ON   | 0 ~ 20mA  |             |
|                   | OFF             | ON   | OFF  | OFF  | OFF  | ON   | 0 ~ 10V   |             |
|                   | ON              | OFF  | OFF  | ON   | OFF  | OFF  | ± 25mV    |             |
|                   | OFF             | ON   | OFF  | ON   | OFF  | OFF  | ± 50mV    |             |
|                   | OFF             | OFF  | ON   | ON   | OFF  | OFF  | ± 100mV   |             |
|                   | ON              | OFF  | OFF  | OFF  | ON   | OFF  | ± 250mV   |             |
|                   | OFF             | ON   | OFF  | OFF  | ON   | OFF  | ± 500mV   |             |
|                   | OFF             | OFF  | ON   | OFF  | OFF  | OFF  | ± 1V      |             |
|                   | ON              | OFF  | OFF  | OFF  | OFF  | OFF  | ± 2.5V    |             |
|                   | OFF             | ON   | OFF  | OFF  | OFF  | OFF  | ± 5V      |             |
|                   | OFF             | OFF  | ON   | OFF  | OFF  | OFF  | ± 10V     |             |

★Remark: After DIP switches are set up, it will be effective once the PLC is powered.


## Remark for Analog input module

When input correction on PM 235-0KD22-0XA0 Firstly we use a voltage source or a current source to input "0" signal to one input terminal, and regulate OFFSET Potentiometer till its read number is "0". Then input a signal of full-scale value to another input terminal, and regulate GAIN Potentiometer till its read number is "32000".

## Specifications:

| Model                        | EM231<br>2 inputs,RTD  | EM231<br>4 inputs,RTD  |
|------------------------------|--|--|
| Product Picture              |  |  |
| Product Description          | 2AI RTD temperature measurement, Resolution:16bits, Optical isolation w ith high immunity          | 4AI RTD temperature measurement, Resolution:16bits, Optical isolation w ith high immunity          |
| Technical Specification      |  |  |
| From bus current consumption | 45mA   | 45mA   |
| From L+ current consumption  | 20mA   | 20mA   |
| Pow er loss                  | 1W   | 1W   |
| Number of analog inputs      | 2  | 4  |
| Input type                   | Refer to ground RTD  | Refer to ground RTD  |
| Common-mode rejection        | >120dB@120V AC   | >120dB@120VAC  |
| Wire loop resistance(Max)    | 20 Ω   | 20 Ω   |
| Module update time           | 405ms  | 800ms  |
| Data word format             | Resistance:0~+27648  | Resistance:0~+27648  |
| Input range                  | RTD:Pt100,Pt200,Pt500,Pt1000,Pt10000,Ni100,Ni120,Ni1000,Cu10(9.035)<br>Resistance: 150Ω, 300Ω,600Ω | RTD:Pt100,Pt200,Pt500,Pt1000,Pt10000,Ni100,Ni120,Ni1000,Cu10(9.035)<br>Resistance: 150Ω, 300Ω,600Ω |
| Measuring principle          | Sigma→delta  | Sigma→delta  |
| Resolution                   | 15+1 Sign bit  | 15+1 Sign bit  |
| Basic tolerance              | 0.1%FS   | 0.1%FS   |
| Isolation (field to logic)   | >500V  | >500V  |
| 24VDC supply voltage range   | 20.4~28.8V DC  | 20.4~28.8V DC  |
| Dimensions(W x H x D)(mm)    | 71.2×80×62   | 71.2×80×62   |
| Order Number                 | 231-7PB22-0XA0   | 231-7PC22-0XA0   |

## Wiring Diagram



231-7PB22-0XA0

231-7PC22-0XA0